

The definitive guide to switch atmosphere(mixed) custom firmware

Prep Work:

1. R4S Dongle



2. R4S Jig



3. One MicroSD card.





Let's get started.

I : Download Software

Download link:



II : Format Micro SD Card

Use the option in the picture shown below:

Format USB Drive (H:)	×
Capacity:	
119 GB	~
File system	
exFAT (Default)	~
Allocation unit size	
32 kilobytes	~
Volume label	
Format options	

 $PS\colon$ Switch doesn't support exFAT by default. Before next step, please put micro SD card

inside switch SD card slot. System will prompt to update system patch after power on. You can connect to internet to update exFAT support. Offline update exFAT support is possible, please Google "How to install the exFat Update without updating your Switch".



${\rm III}$: Extract downloaded zip file to root of SD file and put micro SD card

into switch SD card slot.

Make sure the contents in the SD card like this:



IV : Boot customer firmware

1. Turn off your switch console.

Hold power button till the following screen appear, press Power Off.

	C) Sleep Mode	
	Restart	
	Turn Off	
ames	Close	



2. Remove the right Joycon from the switch console and slide the jig tool all the way down to the end.



3. Insert the R4S dongle into the USB-C port on the bottom of the Switch.





4. Hold the VOL + button and power button to turn on the Switch, the red led on the dongle will be light, and the system should boot into the custom firmware.





Install NSP game

1. Power off console, remove SD card from console, put SD card into PC. Copy NSP files to the root of SD card.

	bootloader
	EdiZon
	ftpd
	modules
	ReiNX
	switch
	tinfoil
	xor.play.json
	hekate_ipl.ini
	hbmenu.nro
BMP	bootlogo.bmp
	Shovel Knight.nsp
	EnterTheGungeon.nsp

- 2. Insert SD card to the console, repeat **step IV** boot up system.
- 3. Click "Album"





Click "Tinfoil" in the next screen as shown in the picture below:



4. Tinfoil UI will be shown as following:





www.r4i-sdhc.com

- 5. Select Title Management->Install NSP-> devmenu.nsp.
 - Wait for Done! appear which means installation finished successfully.



6. Go back home screen by press Home button. A new devmenu icon will come out. Open it.





7. Now devmenu will come out, click on "install from SD", NSP files list shows the files inside NSP folder of SD card

DevMenu(Ap)	p): Application		52% D 10:45
Application	Install from SD Write to	GameCard	
Save Data			
Controller	Hulu ID: 0x0100x860003384000 I Ve	nien: 1.0.144	
Accounts	ACA NEOGEO METAL	SLUG 3	Net Laurchute
Device	D: Del 100matica 1 de 6000 i Ver	No: 1.0.2	
Network	Taiko No Tatsujin Nint	endo Switch VersionI 🗉	Missing Game Card
Sound	MONSTER HUNTER X	X Nintando Switch Ver El	Master Game Cast
Time Test	ID: 0x0100c3800049c000 I Ver	siem 1.3.0	
Debug	2011		Nol Laurchable
Error	-/+: Option	Built-in 21,583.	312 / 27,249,648 KB
Firmware		SD Card 7,501	,984 / 7,756,800 KB

8. Select nsp file from the list, press A to start installation.

nstall Completed]	
d:/NSP/ACA NEO SLUG [0	100ebe002b3e000][v0].n
9,890,304 / 89,890,304 (1)	00.0%)
0	ose



9. Go back home screen by press Home button. Close devmenu, A game icon will come out.





www.r4i-sdhc.com

Install XCI game

1. Down free DEMO game, US version of "Shining Resonance Refrain Demo" is recommended.



 Convert download xci file in PC using one-key-conversion tool. (download link:<u>https://bit.ly/2MVypgD</u> or <u>https://bit.ly/2o2XdZx</u>)

Note:

i. One-key-conversion tool doesn't support non standard characters and space, make sure the xci files and target npdm files and directories don't have non standard characters and space.

Ii. When conversion finish, Title id will be shown. If no Title id shown, means either wrong xci file, or the file name or directory name problem as described in note i.

arget ti	tle to be replaced	XCI directory path	
Size	Name	E:\SUN\SWITCH_GAME Select	
3.7 GB hr-alera.xci	Output directory path		
	E:\SUN\SWITCH_GAME Select		
	hactool. exe path		
	E:\SUN\SWITCH_GAME\XCI2TitleConverter2.C Select		
	keys. txt path		
	E:\SUN\SWITCH_GAME\XCI2TitleConverter2.C Select		
	Target title to be replaced Title ID Title		
	Shining Resonance Refrain Demo - 01006EE00AE38000		
		Start	

R4^S

3. If there is no error, a new title id directory will be created.

D1006EE00AE38000	2018/8/1 14:33	文件夹
XCI2TitleConverter2.0	2018/8/1 14:33	文件夹
hr-alera.xci	2018/7/13 12:12	XCI 文件

4. Copy newly created title id directory to the Backups directory of SD.

퉬 atmosphere	2018/8/1 9:28
퉬 Backups	2018/8/1 9:28
퉬 EdiZon	2018/8/1 9:31
퉬 modules	2018/8/1 9:31
🍌 Nintendo	2018/8/1 9:31
NSP NSP	2018/8/1 9:31
🔒 switch	2018/8/1 9:31
퉬 tinfoil	2018/8/1 9:31
	2018/7/31 17:59
💼 bootlogo.bmp	2018/7/5 21:38
hbmenu.nro	2018/7/22 0:39
hekate_ipl.ini	2018/7/22 14:35
📄 info.json	2018/3/2 18:20
manifest.install	2018/5/29 21:55

5. Insert SD card to the console, repeat **step IV** boot up system.

6. Click Album, then click "mod_Plague".





www.r4i-sdhc.com

7. The following screen will appear.



Press "X" key, then select"Shining Resonance Refrain Demo".



8. Press "A" key, Select the newly copied title id folder.



10. When the screen shown below appear, installation is complete successfully. Congratulations!

Press "HOME", load new game by select 'Shining Resonance Refrain Demo' enjoy! !

